

SPECIFICATION

TO ALL WHOM IT MAY CONCERN:

BE IT KNOWN THAT WE, Sung Uk Moon, a citizen of Korea residing at Yokosuka-shi, Kanagawa Japan, Takehiro Nakamura, a citizen of Japan residing at Yokosuka-shi, Kanagawa Japan, Minami Ishii, a citizen of Japan residing at Yokohama-shi, Kanagawa Japan and Masafumi Usuda, a citizen of Japan residing at Yokosuka-shi, Kanagawa Japan have invented certain new and useful improvements in

TRANSMISSION CONTROLLER, WIRELESS BASE STATION,
AND METHOD OF CONTROLLING TRANSMISSION RATE

Of which the following is a specification:-

TITLE OF THE INVENTION

TRANSMISSION CONTROLLER, WIRELESS BASE STATION,
AND METHOD OF CONTROLLING TRANSMISSION RATE

5 BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention generally relates to
a transmission controller, a wireless base station and
a method of controlling a transmission rate, and
10 particularly relates to a transmission controller, a
wireless base station and a method of controlling a
transmission rate, in which a downlink transmission
rate of a mobile station is controlled based on
downlink transmission quality.

15 2. Description of the Related Art

In the WCDMA (Wideband Code Division Multiple
Access) method being adopted in third generation mobile
communications systems, a communications channel
engaging in communications receives interference
20 (Multiple Access Interference: MAI) from other
communications channels and interference from multi-
paths in the communications channel itself (Multi-Path
Interference). A mobile communications system to which
this WCDMA method is applied is a system in which
25 such interference as described above limits the
subscriber capacity of the system. Therefore,
transmitting with the least power possible while
allowing each individual channel to achieve
predetermined quality enables an increase of the
30 wireless circuit capacity.

In the current WCDMA method, a transmission
power control method which enables an increase of the
wireless circuit capacity by maintaining the

transmission power to a necessary minimum is used, the transmission power control method further accounting for conserving power.

5 The transmission power control method used in the WCDMA method may be categorized into open-loop transmission power control (open-loop power control) and closed-loop transmission power control (closed-loop power control).

(Open-loop transmission power control)

10 In a mobile communications system, an uplink common-control channel is not a channel used in a pair of uplink and downlink circuits, so that applying closed-loop control is not possible. Therefore, open-loop transmission power control is used. In a mobile station, the downlink propagation loss using a downlink common-control channel is estimated so that uplink transmission power is determined based on that estimated value. Also for each individual channel to which closed-loop transmission power control is applied, 15 an initial transmission power setting is usually determined using the open-loop. 20

(Closed-loop transmission power control)

FIG. 6A and FIG. 6B illustrate the concept of closed-loop transmission power control of the uplink and downlink circuits. FIG. 6A illustrates the concept 25 of uplink closed-loop transmission power control, while FIG. 6B illustrates the concept of downlink closed-loop transmission power control. In closed-loop transmission power control, for both the uplink and downlink 30 circuits, a measurement at the receiving side (a wireless base station 30, 40, or a mobile station 15, 16) of the quality of the communications channel is performed and a transmission power control (TPC) bit

is transmitted using a return channel (or a control channel of layer 1 transmitted with a communications channel) so that a communications channel receiving transmission fulfills a desired quality. In other words, 5 when a quality value of the communications channel measured as described above is greater than a target value, a transmission-power control bit (UP) which raises the transmission power is transmitted, whereas, when the quality value measured is less than the 10 target value, a transmission-power control bit (Down) which lowers the transmission power is transmitted. Then, the mobile station and the wireless base station which receive the transmission-power control bit as described above change the transmission power based on 15 that received transmission power control bit.

FIG. 7 is a receiving-block diagram of dual closed-loop control applied to a wireless base station and a mobile station using the WCDMA method. This dual closed-loop control consists of 2-stage loops of 20 1) inner-loop control and 2) outer-loop control. Below, operations of 1) the inner-loop control and 2) the outer-loop control are described.

(Inner-loop control)

In the inner-loop transmission power control 25 of an uplink (or a downlink) communications channel, in a wireless base station (or a mobile station) a received baseband signal is despread at a despreading section 51 and Rake-received at a Rake receiver 52 so as to have the received SIR (Signal-to-Interference 30 Ratio) measured at a SIR-measuring section 53. Then, the received SIR measured and a target SIR from a target SIR section 55 are compared at a comparative-decision section 54 so that, at a TPC-bit generating

section 56, for a received SIR measured below the target SIR an "UP" command, and for the received SIR measured equal to or above the target SIR a "DOWN" command, is generated as a TPC bit so as to be mapped to a transmitting-side control channel and transmitted. At a mobile station (or a wireless base station), the TPC bit is received so as to cause a change of the transmission power by 1 dB based on the decoded result. Such closed-loop transmission power control is performed every slot period (0.667 ms).

(Outer-loop transmission power control)

In the inner-loop control as described above, while control so as to cause the received SIR of the communications channel to be a certain target value is performed, in the outer-loop control, a target SIR is controlled so as to cause the communications quality (for example, BER: Bit Error Rate, BLER: Block Error Rate, or FER: Frame Error Rate) to be a certain target value. More specifically, at a long-term quality measuring section 57, the communications quality as described above is measured for a certain long term (from a few 100 milliseconds to a few seconds) so that the measured value and a target quality value from a target quality section 58 are compared at a comparative decision section 59. At a target SIR section 55, based on the comparative decision result of a comparative decision section 59, a target SIR is set so as to cause the communications quality as described above to be the target quality.

Thus, in the related art, the transmission power is controlled in accordance with the dual closed-loop control method.

Furthermore, there exists a method of

appropriately controlling a transmission rate depending on the circuit state so as to enable appropriate control of the transmission power of a wireless base station relative to a mobile station (for example, 5 refer to Patent Document 1).

Patent Document 1

JP2003-023395A

Non-Patent Document 1

3rd Generation Partnership Project Technical
10 Specification Group Radio Access Network, 23.214
Physical layer procedure (FDD), September, 2002.

As described above, in the mobile communications system based on the CDMA method, the transmission power control which maintains the
15 receiving quality to a predetermined quality is mandatory. On the other hand, changing transmission channel characteristics causing a degradation in the transmission quality (or a degradation of the propagation environment) causes the transmission power
20 value necessary to fulfill a predetermined receiving quality to be increased to a predetermined value (or the maximum transmission power) so that a further raising of the transmission power is not possible when the predetermined value is reached. Therefore, while in
25 the related art, control is performed in whereby the downlink transmission rate is lowered so that the transmission power capacity of a wireless base station is not exceeded, in such a case, there is a problem in that the processing burden at the time of the
30 transmission rate control becomes large when simultaneously controlling all mobile stations requiring control.

Furthermore, in the method of controlling the

transmission rate as described in Patent Document 1,
the fact that a control process to lower the
transmission rate at the time of a poor circuit state
is performed, thereby causing appropriate control of
5 the transmission power of a wireless base station
relative to a mobile station, is disclosed. However,
this related-art method does not reduce the processing
burden at the time of controlling the transmission
rate.

10

SUMMARY OF THE INVENTION

It is a general object of the present
invention to provide a transmission controller, a
wireless base station and a method of controlling a
15 transmission rate, that substantially obviate one or
more problems caused by the limitations and
disadvantages of the related art.

In light of the problems as described above,
it is a more particular object of the present
20 invention to provide a transmission controller, a
wireless base station and a method of controlling
transmission rate, that enable a reduction of the
processing burden at the time of controlling a downlink
transmission rate of a mobile station even when the
25 transmission power increases due to a degrading
propagation environment and the like.

According to the invention, a transmission
controller which controls multiple downlink transmission
rates corresponding to multiple communications terminals
30 based on multiple downlink transmission qualities
corresponding to the communications terminals includes
a transmission-quality obtaining unit configured to
obtain the downlink transmission qualities of the

communications terminals, a communications-terminal selecting unit configured to select out of the communications terminals one or more communications terminals which cause to change corresponding one or
5 more downlink transmission rates in accordance with the downlink transmission qualities obtained at the transmission-quality obtaining unit, and a transmission-rate changing unit which causes to change one or more downlink transmission rates corresponding to one or
10 more communications terminals selected at the communications-terminal selecting unit.

The transmission controller in an embodiment of the invention enables a reducing of the processing burden when controlling the transmission rate so as to
15 facilitate a control of other parameters.

According to another aspect of the invention, a wireless base station which controls multiple downlink transmission rates corresponding to multiple mobile stations based on multiple downlink transmission
20 qualities corresponding to the mobile stations includes a transmission-quality obtaining unit configured to obtain the downlink transmission qualities of the mobile stations, a mobile-station selecting unit configured to select out of the mobile stations one
25 or more mobile stations which cause to change corresponding one or more downlink transmission rates in accordance with downlink transmission qualities obtained at the transmission-quality obtaining unit, and a transmission-rate changing unit which causes to
30 change one or more downlink transmission rates corresponding to one or more mobile stations selected at the mobile-station selecting unit.

The wireless base station in an embodiment

of the invention enables a reduction of the processing burden when controlling the transmission rate so as to facilitate control of other parameters.

According to another aspect of the invention,
5 a method of controlling transmission rates which controls multiple downlink transmission rates corresponding to multiple communications terminals based on multiple downlink transmission qualities corresponding to the communications terminals includes
10 the steps of, obtaining the downlink transmission qualities of the communications terminals, comparing corresponding values of the downlink transmission qualities obtained with a predetermined quality, selecting, when at least one of the downlink
15 transmission qualities is determined to fall below a predetermined quality, as one or more communications terminals which cause to change corresponding one or more downlink transmission rates, at least one communications terminal out of the communications
20 terminals with corresponding downlink transmission quality falling below the predetermined quality, and changing the downlink transmission rate of the at least one communications terminal selected.

The method of controlling transmission rates
25 in an embodiment of the invention enables a reduction of the processing burden when controlling the transmission rates so as to facilitate control of other parameters.

Other objects and further features of the present invention will be apparent from the following
30 detailed description when read in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram of a mobile communications system to which a method of controlling a transmission rate according to an embodiment 1 of the present invention is applied;

5 FIG. 2 is a functional block diagram illustrating a configuration of a wireless controller according to the embodiment 1 of the present invention;

10 FIG. 3 is a flowchart illustrating a transmission-rate control process at the wireless controller according to the embodiment 1 of the present invention;

15 FIG. 4 illustrates one example of a transmission-power control table according to an embodiment 2 of the present invention;

 FIG. 5 is a sequence diagram illustrating a transmission-rate control process according to an embodiment 3 of the present invention;

20 FIG. 6A is a schematic diagram illustrating the concept of closed-loop transmission power control of an uplink circuit;

 FIG. 6B is a schematic diagram illustrating the concept of closed-loop transmission power control of a downlink circuit; and

25 FIG. 7 is a receiving-block diagram of dual closed-loop control applied to a wireless base station and a mobile station using the WCDMA method.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

30 In the following, embodiments of the present invention are described with reference to the accompanying drawings.

 FIG. 1 is a block diagram of a mobile

communications system to which a method of controlling a transmission rate according to an embodiment 1 of the present invention is applied.

In FIG. 1, this mobile communications system
5 consists of a wireless base station 10, multiple mobile stations 11 through 14 residing in an area of the wireless base station 10, and a wireless controller 20 controlling the wireless base station 10 as described above. For each of the mobile stations
10 11 through 14 as described above, transmission power control is performed between the wireless base station 10 and the wireless controller 20.

FIG. 2 is a functional block diagram illustrating a configuration of the wireless controller
15 20 according to the embodiment 1 of the present invention.

In FIG. 2, this wireless controller 20 consists of a transmission-quality measuring section 21, a transmission-quality comparing section 22, a
20 transmission-rate control section 23, a mobile-station selecting section 24, and a transmission-power control section 25.

The transmission-quality measuring section 21, based on measured information of the transmission
25 quality received from a mobile station (for example, a Signal-to-Noise Ratio, a received power level, a Signal-to-Interference Ratio, a signal-error rate), obtains the downlink transmission quality. The transmission-quality comparing section 22 compares a
30 predetermined quality value with a measured value of the downlink transmission quality which is sent from the transmission-quality measuring section 21 so as to send the comparison result to the mobile-station

selecting section 24. The mobile-station selecting section 24, from the result as described above, selects, based on predetermined criteria, a mobile station to be the target for controlling the transmission rate, from mobile stations having reported the fact that the downlink transmission quality is less than or equal to the predetermined quality, so as to report that selected result to the transmission-rate control section 23. The transmission-rate control section 23 changes the downlink transmission rate relative to the mobile station selected at the mobile-station selecting section 24, so as to send the changed transmission-rate information to the transmission-power control section 25. The transmission-power control section 25 in accordance with the information of the transmission rate which is sent from the transmission-rate control section 23 controls the transmission power so as to transmit a downlink signal.

FIG. 3 is a flowchart illustrating a transmission-rate control process in the wireless controller 20 according to the embodiment 1 of the present invention.

In FIG. 3, the transmission-quality measuring section 21 obtains, from each of the mobile stations 11 through 14, as downlink transmission quality information, a Signal-to-Noise Ratio (below abbreviated as SN Ratio) (Step S1). For example, the SN Ratio of the downlink circuit measured at each of the mobile stations 11 through 14 is assumed as follows:

Mobile station	Measured SN Ratio (in dBs) result of the
----------------	--

		downlink circuit
	1) Mobile station 11	5 dB
	2) Mobile station 12	0 dB
	3) Mobile station 13	-5 dB
5	4) Mobile station 14	-10 dB

The transmission-quality comparing section 22, upon receiving the measured value of the downlink-circuit SN Ratio from each of the mobile stations 11 through 14, compares the measured values with a predetermined transmission quality (in this case, a predetermined SN Ratio) (Step S2). Herein, assuming the predetermined SN Ratio as "-3 dB", there are 2 mobile stations with a SN Ratio below the predetermined value, the mobile station 13 (with a SN Ratio of -5 dB) and the mobile station 14 (with a SN Ratio of -10 dB) so that these are extracted as mobile-station selecting targets (YES in Step S2). In Step S2, if no mobile stations with a SN Ratio below the predetermined SN Ratio (NO in Step S2) exist, a measured value of the downlink transmission quality of each of the mobile stations 11 through 14 is obtained again, returning to Step S1.

Thus, as described in the above, the mobile stations 13 and 14 which are selecting targets extracted at the transmission-quality comparing section 22 are reported to the mobile station-selecting section 24 (Step S3) and selected according to predetermined criteria, for example, a transmission rate of the mobile station (Step S4). For example, assuming that the transmission rates of the mobile stations 13 and 14 are respectively 128 kbps and 64 kbps, the mobile station with a higher transmission rate, or the mobile station 13, is selected. Thus, when the mobile station 13 is selected at the mobile-station selecting section

24, that selected mobile station information (in this case, information indicating the mobile station 13 and information indicating the current transmission rate of the mobile station 13) is sent to the transmission-
5 rate control section 23 so that at the transmission-
rate control section 23, a control process which reduces the transmission rate of the mobile station 13 is performed (Step S5). For example, the transmission rate is lowered from 128 kbps to 64 kbps. In other
10 words, for the downlink circuit with a notable degradation of transmission quality due to multi-path fading and the like, communications with the transmission rate kept high are wasteful, only consuming much power. Thus, when the transmission
15 quality is degraded, the transmission rate is lowered so as to suppress the transmission volume of data, thereby reducing the transmission power.

In the transmission-power control section 25, the transmission power is adjusted in accordance with
20 the transmission rate changed at the transmission-rate control section 23 (in this case, 64 kbps), so that a transmission of a downlink signal is performed (Step S6).

As described above, according to the present
25 embodiment, as a mobile station having the downlink transmission quality equal to or below a certain level is selected so that the downlink transmission rate of that selected mobile station is controlled, the transmission rate is lowered for a mobile station with
30 a low transmission efficiency relative to the amount of power consumption. In other words, there is no longer a need to oversee so as to control all of the base stations as in the related art. Therefore, a

reduction of the processing burden at the time of controlling the transmission rate so as to facilitate the process of controlling others is enabled.

While in the embodiment 1 as described above,
5 a case of selecting only one mobile station in the descending order of the transmission rate at the mobile-station selecting section 24 as a mobile station targeted for the transmission rate control is described, multiple mobile stations may be selected in the
10 descending order of the transmission rate. For example, both mobile station 13 and mobile station 14 may be selected in that order.

Also, in the embodiment 1 as described above, while a case of the mobile-station selecting section
15 24 selecting a mobile station targeted for control of the transmission rate based on the transmission rate of the mobile station is described, the present invention is not limited to such selection criteria. For example, it may take a form such as to select
20 mobile stations based on the received-quality values reported from the mobile stations. In that case, mobile stations are selected in the ascending order of the receiving quality. Also, in addition to those as described above, a selection of mobile stations may be
25 based on the travelling speed or the arrival time (or the order) of the received quality values reported as described above, or may be selected randomly.

Further, while control of the transmission rate according to the embodiment 1 describes a case
30 of reducing the downlink transmission rate from 128 kbps to 64 kbps, control may be performed so as to cause changes to successively lower transmission speeds (for example: 128 kbps to 64 kbps to 32 kbps).

Furthermore, in the embodiment 1, while a case of the transmission-quality measuring section 21 obtaining the downlink transmission quality reported from each of the mobile stations is described, it may
5 take a form so that the transmission-quality measuring section 21 measures and obtains the downlink quality of transmission to the mobile stations so as to obtain the transmission quality.

(Variations)

10 The present invention is not limited to the above embodiment, enabling a number of variations.

(Embodiment 2)

FIG. 4 is a diagram illustrating one example of a transmission-power control table. The
15 transmission-power control table as described above is referred to when the mobile-station selecting section 24 selects the number of the mobile stations. In the present embodiment 2, the mobile-station selecting section 24 when selecting a mobile station targeted
20 for control of the transmission rate determines the number of mobile stations targeted for control of the transmission rate, determines the number of the mobile stations based on a ratio of a measured value of the total transmission power (the total transmission power
25 of the wireless base station) relative to a predetermined power value (a threshold value). In the transmission-power control table, the ratio of the predetermined threshold value to the measured value of the total transmission power of multiple mobile
30 stations n , and the number of mobile stations are correlated so as to be controlled. For example, in a case that the predetermined power value is 30 dBm, more mobile stations are selected when the measured

value of the total transmission power is 28dBm than when the value is 25 dBm. In other words, when the measured value of the total transmission power of the multiple mobile stations n approaches the predetermined power value, more power resources of the wireless base station are consumed; in such a case, as more mobile stations are selected, the transmission rate is lowered so as to suppress consumption of power resources of the wireless base station. Hereby, efficient use of the power resources of the wireless base station is enabled.

In the embodiment 2 as described above, while a case of determining the number of mobile stations changing the downlink transmission rate from the relationship between the measured value of the total transmission power of the multiple mobile stations and the predetermined power value is described, the present invention is not limited to this case. For example, it may take a form such that a list of mobile stations reordered in the descending order of the transmission power is controlled in the above transmission-power control table, so as to select the mobile stations up to the top m -th in terms of the transmission power depending on the measured total transmission power value of the mobile stations n .

Further, in the embodiment 1 of the present invention, while a case of selecting a mobile station with the downlink transmission quality below a predetermined quality as the mobile station targeted for transmission rate control is described, it may take a form such that a mobile station with the downlink transmission quality exceeding a predetermined quality is selected as a mobile station targeted for

transmission rate control, and control so as to raise the transmission rate of that selected mobile station. Furthermore, that case is limited to a case in which there is an availability of power resources of the
5 wireless base station.

Furthermore, it may take a form such that mode 1 and mode 2 are adaptively switched, where the mode 1 corresponds to selecting a mobile station with a good downlink transmission quality when there is
10 relative availability of power resources, and the mode 2 corresponds to selecting a mobile station with a poor downlink transmission quality when there is no availability of power resources.

Furthermore, while a case of the wireless
15 controller serving to control the transmission rate according to the embodiment of the present invention is described, as a matter of course, the transmission rate control as described above may be performed by the wireless base station.

20 (Embodiment 3)

FIG. 5 is a sequence diagram illustrating a transmission-rate control process according to an embodiment 3 of the present invention. In this example, MS1 (a mobile station), MS2, and MS3 respectively
25 communicate at 128 kbps, 128 kbps, and 64 kbps, each MS measures the downlink transmission quality, and transmits a request for changing the transmission rate to a BS (a wireless base station) when a measured value of the transmission quality is less than or
30 equal to a predetermined value. Herein, a request for change in the transmission rate as described above is included in the measured transmission quality value information reported from the MS-side. BS, upon

receiving the request for change in the transmission rate from MS2, performs a control process causing a reduction of the transmission rate of MS2 (from 128 kbps to 64 kbps, in this example) so as to start the
5 transmission of a downlink signal at the transmission power in accordance with the changed transmission rate.

According to the embodiment 3 as described above, as there is no need to select, at the BS-side, a MS targeted for transmission rate control, enabling
10 a reduction of the processing burden related to transmission-rate control at the BS. Further, at the MS-side, as a request for change in the transmission rate (for example, activating a flag bit) is merely included in the reporting information periodically
15 reported to BS, there is no need to newly exchange control information at a wireless term in order to cause a change in the transmission rate.

Furthermore, in the embodiment 3, while a case of performing control of the transmission rate at
20 the BS is described, as a matter of course, the control process of the transmission rate may be performed at a high-level node of the BS.

The present application is based on Japanese Priority Patent Application No. 2003-109352 filed April
25 14, 2003, with the Japanese Patent Office, the entire contents of which are hereby incorporated by reference.